

INTERFACING NAVMAN VHF 7100/7200 WITH A GPS

This is the recommended way to connect the new VHF series (7100/7200) to Tracker 5000 series, or other brands of GPS/Plotter. Most lower cost GPS/Plotters do not have a dedicated NMEA out – wire. This connection is usually made internally to the negative or 0v power supply connection. Therefore to complete the connection at the VHF end it is necessary to connect the green to the negative power connection of the VHF. The connection will only work if the Tracker and the VHF are connected to the same 0v supply system. The Tracker must also have the Autopilot output enabled and at least GLL and RMC data set to on. This routine is performed via the setup menu and the section called 'coms'.

